

# S19955 S19956 S19957 Ballast Compatible List

No.	Ballast Brand	Model No.	Start Type	Max Loading QTY	Compatible (Y/N/N/A)			
					1 LAMP		2 LAMPS	
					120VAC	277VAC	120VAC	277VAC
1	OSRAM	QHE 2X28T5/UNV PSN	Instant Start	2	Y	Y	Y	Y
2	GE	GEC140MAX-A	Instant Start	1	Y	N	N/A	N/A
3	GE	GEC240MAX-A	Instant Start	2	Y	Y	Y	Y
4	GE	GE232MAX-G-N	Instant Start	2	N	N	Y	Y
5	GE	GE232MAX-G-N-DIYB	Instant Start	2	Y	Y	Y	Y
6	AccuStart	B228PUNV-C	Instant Start	2	Y	Y	Y	Y
7	QUICKTRONIC	QTP 2x26CF/UNV DM	Programmed Rapid Start	2	Y	Y	Y	Y
8	Sylvania	QTP 2x26CF/UNV DM PEM	Programmed Rapid Start	2	Y	Y	Y	Y
9	Osram	QTP 2x26/32/42CF/UNV DM PEM	Programmed Rapid Start	2	N	N	Y	Y
10	FLEXCONNECT	E21338-UV-TDE-FLX	Program Start	2	Y	Y	Y	Y
11	Wellypower	ES2T5282E03	-	2	N/A	N	N/A	Y

No.	Ballast Brand	Model No.	Start Type	Max Loading QTY	Compatible (Y/N/N/A)			
					Charging		Emergency	
					120VAC	277VAC	120VAC	277VAC
1	IOTA	I-160	Emergency Ballast	2	Y	Y	Y	Y

**Y: Compatible**  
**N: Incompatible**  
**N/A: Not applicable**

**When working with electronic ballast please check the compatibility list first!**  
**If you couldn't find your ballast on the list then bypass the fixture, or contact us please!**  
**Do not install the LED tube with the ballast which is not on the ballast compatibility list, risk of firing!**