

S19958 S19959 S19960 Ballast Compatible List

No.	Ballast Brand	Model No.	Start Type	Max Loading QTY	Compatible (Y/N/N/A)			
					1 LAMP		2 LAMPS	
					120VAC	277VAC	120VAC	277VAC
1	GE	GEC240MAX-A	Instant Start	2	Y	Y	Y	Y
2	KEYSTONE	KTEB-126-1-TP	Rapid Start	1	Y	N/A	N/A	N/A
3	QUICKTRONIC	QTP 2x26CF/UNV DM	Programmed Rapid Start	2	Y	Y	Y	Y
4	GE	GEC242-MVPS-3W	Program Start	2	Y	Y	Y	Y
5	Sylvania	QTP 2x26CF/UNV DM PEM	Programmed Rapid Start	2	Y	Y	Y	Y
6	Osram	QTP 2x26/32/42CF/UNV DM PEM	Programmed Rapid Start	2	Y	Y	Y	Y
7	OSRAM	QTP 2x26/32/42CF/UNV DM	Programmed Rapid Start	2	N	N	Y	Y
8	Triad	C2642UNVME	Programmed Rapid Start	2	Y	Y	Y	Y
9	KEYSTONE	KTEB-226-UV-RS-DW	Rapid Start	2	N	N	Y	Y
10	STANDARD	ED2150-347BS	Program Start	2	N/A	N	N/A	Y
11	OSRAM	QTP 2x26CF/UNV DM	Programmed Rapid Start	2	Y	Y	Y	Y

No.	Ballast Brand	Model No.	Start Type	Max Loading QTY	Compatible (Y/N/N/A)	
					1 LAMP	2 LAMPS
					347VAC	347VAC
1	STANDARD	ED2150-347BS	Program Start	2	N	Y

Y: Compatible
N: Incompatible
N/A: Not applicable

When working with electronic ballast please check the compatibility list first!
If you couldn't find your ballast on the list then bypass the fixture, or contact us please!
Do not install the LED tube with the ballast which is not on the ballast compatibility list, risk of firing!