

# S19961 S19962 S19963 Ballast Compatible List

No.	Ballast Brand	Model No.	Start Type	Max Loading QTY	Compatible (Y/N/N/A)			
					1 LAMP		2 LAMPS	
					120VAC	277VAC	120VAC	277VAC
1	GE	GEC140MAX-A	Instant Start	1	Y	Y	N/A	N/A
2	GE	GEC240MAX-A	Instant Start	2	Y	Y	Y	Y
3	Keystone	KTEB-126-1-TP	Rapid Start	1	Y	N/A	N/A	N/A
4	QUICKTRONIC	QTP 2x26CF/UNV DM	Programmed Rapid Start	2	Y	Y	Y	Y
5	GE	GEC242-MVPS-3W	Program Start	2	Y	Y	Y	Y
6	Sylvania	QTP 2x26CF/UNV DM PEM	Programmed Rapid Start	2	Y	Y	Y	Y
7	Osram	QTP 2x26/32/42CF/UNV DM PEM	Programmed Rapid Start	2	Y	Y	Y	Y
8	OSRAM	QTP 2x26/32/42CF/UNV DM	Programmed Rapid Start	2	N	N	Y	Y
9	Triad	C2642UNVME	Programmed Rapid Start	2	Y	Y	Y	Y
10	KEYSTONE	KTEB-226-UV-RS-DW	Rapid Start	2	N	N	Y	Y
11	OSRAM	QTP 2x26CF/UNV DM	Programmed Rapid Start	2	Y	Y	Y	Y

No.	Ballast Brand	Model No.	Start Type	Max Loading QTY	Compatible (Y/N/N/A)	
					1 LAMP	2 LAMPS
					347VAC	347VAC
1	TRIAD	C2642/347ME	Programmed Rapid Start	2	Y	Y
2	TRIAD	ED2150-347BS	Program Start	2	N	Y

**Y: Compatible**  
**N: Incompatible**  
**N/A: Not applicable**

**When working with electronic ballast please check the compatibility list first!**

**If you couldn't find your ballast on the list then bypass the fixture, or contact us please!**

**Do not install the LED tube with the ballast which is not on the ballast compatibility list, risk of firing!**