

Wiring Instructions for 86/500, 86/501.

Warning: Turn off electrical power at the fuse or circuit breaker panel before wiring motion sensor to the light fixture.

Step 1: Verify the input supply voltage is correct by comparing it with the motion sensor and light fixture label information.

Step 2: Secure the motion sensor ½" knuckle mount arm to the light fixture or flood lights mounting plate or housing.

Step 3: Connect the black wire lead from the motion sensor to the main load lead (L) leading from the main AC input circuit.

Step 4: Connect the Yellow wire leading from the motion sensor to the Black wire leading from the Fixture or flood lights.

Step 5: Connect the white wire lead from the motion sensor to the white wire leading from the main ac circuit and white wire's leading from the light fixture or flood lights.

Step 6: Restore power at the source and the installation is complete.

