



LED 4-Pin PL Electronic Dimmer Compatibility Chart

Ballast Brand*	Ballast Model No.	Dimmer Brand*	Dimmer Model No.	Dimming Type	# Of Lamps	1 Lamp		2 Lamps	
						120V	277V	120V	277V
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	DIVA DVELV-300P	Triac	2	F	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	SKYLARK CTCL-153P	Triac	2	S	NA	S	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	SKYLARK CT-603PG	Triac	2	L,H	NA	H	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	SKYLARK S-600P	Triac	2	S @min	NA	S @min	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	Ariadni AY-600P	Triac	2	L,H	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LEVITON	DECORA 6633P	Triac	2	F	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LEVITON	DECORA IPI06	Triac	2	S @min	NA	S @min	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	DIVA DVCL-153P	Triac	2	F	NA	F	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	NOVQT NTELV-300	Triac	2	F	NA	L	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	DIVA DVLV-603P	Triac	2	L	NA	L	NA
Philips-Advance	REB-2S26-M1-LS-DIM	LUTRON	SKYLARK CT-103P	Triac	2	L	NA	L	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	DIVA DVELV-300P	Triac	2	F @min	NA	F @min	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	SKYLARK CTCL-153P	Triac	2	L	NA	L	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	SKYLARK CT-603PG	Triac	2	F @min	NA	F @min	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	SKYLARK S-600P	Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	Ariadni AY-600P	Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	LEVITON	DECORA 6633P	Triac	2	F @min	NA	F @min	NA
Philips-Advance	REZ-2T42-M3-BS	LEVITON	DECORA IPI06	Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	DIVA DVCL-153P	Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	NOVQT NTELV-300	Triac	2	F @min	NA	F @min	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	DIVA DVLV-603P	Triac	2	F	NA	F	NA
Philips-Advance	REZ-2T42-M3-BS	LUTRON	SKYLARK CT-103P	Triac	2	F @min	NA	F @min	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	DIVA DVELV-300P	Triac	1	NA	NA	L	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	SKYLARK CTCL-153P	Triac	1	NA	NA	L	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	SKYLARK CT-603PG	Triac	1	NA	NA	L	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	SKYLARK S-600P	Triac	1	NA	NA	F @min	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	Ariadni AY-600P	Triac	1	NA	NA	F	NA
Philips-Advance	REZ-1T42-M2-BS	LEVITON	DECORA 6633P	Triac	1	NA	NA	F @min	NA
Philips-Advance	REZ-1T42-M2-BS	LEVITON	DECORA IPI06	Triac	1	NA	NA	F @min	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	DIVA DVCL-153P	Triac	1	NA	NA	F @min	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	NOVQT NTELV-300	Triac	1	NA	NA	L	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	DIVA DVLV-603P	Triac	1	NA	NA	L	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	SKYLARK CT-103P	Triac	1	NA	NA	L	NA
Philips-Advance	REZ-1T42-M2-BS	LUTRON	Ariadni AYCL-153P	Triac	1	NA	NA	L	NA
Philips-Advance	REZ-1T42-M2-BS	LEVITON	DECORA 6842	Triac	1	NA	NA	F	NA
Philips-Advance	VEZ-1T42-M2-LD	LUTRON	NOVQ NA-10-277	Triac	1	NA	NA	NA	L
Philips-Advance	VEZ-2Q26-M2-LD	LUTRON	NOVQ NA-10-277	Triac	1	NA	NA	NA	L
Philips-Advance	VEZ-1T42-M2-BS	LUTRON	NOVQ NA-10-277	Triac	1	NA	NA	NA	L
Philips-Advance	IZT-2S26-M5-LD	LEDdynamics	LUXdrive A019	0-10V	2	F	F	F	F
OSRAM	2x26CF/UNV DIM DM	LEDdynamics	LUXdrive A019	0-10V	2	F	F	F	F

Applies to the following Satco products:	S9850, S9851, S9852, S9853, S9858, S9859, S9860, S9861 S29850, S29851, S29852, S29853,S29858, S29589, S29860, S29861	F	Flicker after >2s start-up (NC)
		N	Acoustic noise >20dB
		L	min LED current > 20% LED current without Dimmer
		H	max LED current < 80% LED current without Dimmer
		NC	Not compatible
		NA	Not applicable

This list is current as of Nov. 2024. We are continuously testing for compatible ballasts. Please check back for updates.

* All trademarks are the property of their respective owners

110 Heartland Blvd.
Brentwood, NY 11717
PH 631-243-2022
FX 631-243-2027

Distribution Centers
New York, Florida,
Texas, Washington,
California, Puerto Rico

National Toll-Free
800-43-SATCO
(800-437-2826)
www.satco.com

Copyright© 2024
Satco Products, Inc.
All Rights Reserved.
Rev: November 15, 2024