

86-238 Add on PIR Sensor



On/off control



Stand-by dimming level



Detection area



Remote control setting



Hold time



12M Highbay altitude



Daylight sensor



Stand-by time

01 Technical data

Operating voltage	12±2V DC
Operating current	30mA
Output	DIM 0-10V
Stand-by power	<0.5W
Brightness	0%-100%/Quick setting: 70%/80%/90%/100%
Hold time	10s/1min/10min/30min
Daylight threshold	10Lux/30Lux/50Lux/100Lux/Disable
Stand-by time	1min/30min/60min/+∞
Stand-by dimming level	10%/20%/30%/50%
Detection angle	≤120°(wall mounted),360°(Ceiling mounted)
Mounting height	Max 12m/39.37ft(ceiling mounted)
Detection range	Radius,2-4m/6.58-13.12ft(ceiling mounted)
Operating temperature	-30°C~+60°C
IP rating	IP65 (Mounted on the light fixture)
Warm-up time	50s

Note:

Default setting: Brightness:100%, Hold time:1min, Stand-by dimming level:20%, Stand-by time:1min, Sensitivity:100%, Daylight: Disable.
(The "Sensitivity" default setting is 100%,and adjustment is not supported.)