

## Ballast Compatible List For 8FT 40W A+B

No.	Ballast Brand	Model No.	Start Type	Max Loading QTY	Compatible (Y/N)			
					1 lamp	2 lamps	3 lamps	4 lamps
1	PHILIPS ADVANCE	ICN-2S110-SC	Rapid Start	2	N	N	N/A	N/A
3	PHILIPS ADVANCE	ICN-2P60-N	Instant Start	2	Y	Y	N/A	N/A
2	PHILIPS ADVANCE	VEL-2P59-S-RH-TP	Instant Start	2	Y	Y	N/A	N/A
4	PHILIPS ADVANCE	IOP-2P59-N	Instant Start	2	N	Y	N/A	N/A
5	GE	GE260IS-MV-N-DIY	Instant Start	2	Y	Y	N/A	N/A
6	GE	GE260ISMV-N-DIYL	Instant Start	2	Y	Y	N/A	N/A
7	GE	GE296HOMVPS-N-DIYB	Rapid Start	2	N	N	N/A	N/A
8	GE	GE296HOMV-N-DIYL	Rapid Start	2	N	N	N/A	N/A
9	GE	GE-159-MAX-N/Ultra	Instant Start	1	N	N/A	N/A	N/A
10	GE	GE259MAX-G-N-DIYB	Instant Start	2	Y	Y	N/A	N/A
11	GE	GE259MAX-L/ULTRA	Instant Start	2	Y	Y	N/A	N/A
12	OSRAM	QTP 2X96T12/UNV IS	Instant Start	2	Y	Y	N/A	N/A
13	OSRAM	QTP 2X96T12HO/UNV RS	Instant Start	2	N	N	N/A	N/A
14	OSRAM	QTP 2X59T8/UNV ISN-SC	Instant Start	2	Y	Y	N/A	N/A
15	OSRAM	QHE 2X59T8/UNV ISN-SC	Instant Start	2	Y	Y	N/A	N/A
16	ACT	ACT2P59ISUNV	Instant Start	2	Y	Y	N/A	N/A
17	Halco	EP259IS/MV	Instant Start	2	Y	Y	N/A	N/A
18	Triad	B259IUNVHP-A	Instant Start	2	Y	Y	N/A	N/A
19	HI HOWARD INDUSTRIES	EP2/59IS/MV/MC/HE	Instant Start	2	Y	Y	N/A	N/A
20	HI HOWARD INDUSTRIES	EP2/110RS/MV/SC	Rapid Start	2	N	N	N/A	N/A

**Note:**

1. Max Loading QTY: Max qty lamps for 1 ballast could be used with
2. Y: The ballast will be compatible when use with such qty lamps
3. N: The ballast will not be compatible when use with such qty lamps
4. N/A: The ballast can not be used with such qty lamps