



A+B 2G11 PLL Lamps Ballast Compatibility Chart

| Ballast Brand*    | Part Number          | # Of Lamps | Start Method | 1 Lamp |       | 2 Lamps |       | 3 Lamps |      | 4 Lamps |      |
|-------------------|----------------------|------------|--------------|--------|-------|---------|-------|---------|------|---------|------|
|                   |                      |            |              | 120V   | 277V  | 120V    | 277V  | 120V    | 277V | 120V    | 277V |
| Accustart         | B254PUNV-D           | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| ACT               | ACT2S54PSUNV         | 2          | IS           | NC     | NC    | ✓       | ✓     | -       | -    | -       | -    |
| Espen             | VE254MVHRP           | 2          | PS           | NC     | NC    | ✓       | ✓     | -       | -    | -       | -    |
| Fulham Racehorse  | RHA-UNV-454-LT5      | 4          | PS           | ✓      | NC    | ✓       | ✓     | ✓       | ✓    | ✓       | ✓    |
| Fulham Racehorse  | RHA-UNV-254-LT5      | 2          | PS           | NC     | -     | ✓       | -     | -       | -    | -       | -    |
| GE Current        | GEC242-MVPS-3W       | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| GE Current        | GEC226-MVPS-3W-L     | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| GE Current        | GE254PS347/480-F     | 2          | PS           | -      | NC    | -       | ✓347V | -       | -    | -       | -    |
| Howard            | EP2/26CF/MV/2        | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| Howard Industries | EP2/54HO/PRS/MV/W/MC | 2          | PRS          | NC     | NC    | ✓       | ✓     | -       | -    | -       | -    |
| Keystone          | KTEB-254HO-UV-PS/A   | 2          | PS           | NC     | NC    | ✓       | ✓     | -       | -    | -       | -    |
| Keystone          | KTEB-242-UV-PS-DW    | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| Keystone          | KTEB-242-UV-RS-DW    | 2          | RS           | NC     | NC    | ✓       | ✓     | -       | -    | -       | -    |
| Osram             | QHE 2x54T5HO/UNV PSN | 2          | PRS          | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| Philips Advance   | HCN-2S54-90C-WL      | 2          | PS           | -      | ✓347V | -       | ✓347V | -       | -    | -       | -    |
| Plusrite          | BAF254PS/MV          | 2          | PS           | NC     | NC    | ✓       | ✓     | -       | -    | -       | -    |
| Prolume           | EP2CF26PS/MV/DC/K    | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| Prolume           | EP2CF42PS/MV/DC/K    | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| Triad             | C2642UNVME           | 2          | RS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |
| Triad             | C2642/347ME          | 2          | PS           | -      | ✓347V | -       | ✓347V | -       | -    | -       | -    |
| Watran            | DBC242MVPSN-K        | 2          | PS           | ✓      | ✓     | ✓       | ✓     | -       | -    | -       | -    |

|                                          |  |                                |    |                  |                  |        |
|------------------------------------------|--|--------------------------------|----|------------------|------------------|--------|
| Applies to the following Satco products: |  | S18416, S18417, S18418, S18419 |    |                  | Ballast Factors: |        |
|                                          |  |                                | NC | Not compatible   | L                | Low    |
|                                          |  |                                | -  | Not applicable   | N                | Normal |
|                                          |  |                                | ** | Dimmable Ballast | H                | High   |

This list is current as of Aug. 2025. We are continuously testing for compatible ballasts. Please check back for updates.

\* All trademarks are the property of their respective owners

|                                                                                  |                                                                                             |                                                                       |                                                                                        |
|----------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|-----------------------------------------------------------------------|----------------------------------------------------------------------------------------|
| 110 Heartland Blvd.<br>Brentwood, NY 11717<br>PH 631-243-2022<br>FX 631-243-2027 | Distribution Centers<br>New York, Florida,<br>Texas, Washington,<br>California, Puerto Rico | National Toll-Free<br>800-43-SATCO<br>(800-437-2826)<br>www.satco.com | Copyright© 2025<br>Satco Products, Inc.<br>All Rights Reserved.<br>Rev: August 29 2025 |
|----------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|-----------------------------------------------------------------------|----------------------------------------------------------------------------------------|