



LED PL BALLAST COMPATIBILITY LIST

Ballast Description					1-Lamp		2-Lamps	
Manufacturer	Model	Start Method	# of Lamps	Lamp Connection	Input Voltage		Input Voltage	
					120V	277V	120V	277V
AC Electronics	CSD-UV42PS	PS	2	Series	✓	✗	✓	✓
AC Electronics	CSS-UV42PS	PS	2	Series	✓	✓	✓	✓
Espen	VE126120MR	PS	1	Parallel	✗	—	—	—
Fulham	NPY-120-126CFL	RS	1	n/a	✗	—	—	—
Fulham	NPY-120-226CFL	RS	2	Series	—	—	✗	—
Fulham	RHA-UNV-226-C	PS	2	Series	✗	✗	✗	✗
Fulham	RHA-UNV-242-C	PS	2	Series	—	—	✓	✗
Fulham	WH2-120-C	IS	1	Parallel	✗	—	—	—
Fulham	WH3-120-C	IS	1	Parallel	✓	—	—	—
Fulham	WH3-120-L	IS	2	Parallel	—	—	✗	—
Fulham	WH3-277-BLS	IS	2	Series	—	✗	—	✗
Hatch	HC218PS/UV/D	PS	1	Series	✗	✗	—	—
Hatch	HC226PS/UV/D	PS	2	Series	✗	✗	✗	✗
Hatch	HC242PS/UV/D	PS	2	Series	—	—	✗	✗
Howard Industries	EP2/42CF/MV/2	PS	2	Series	✗	✗	✗	✗
Keystone	KTEB-126-1-TP	PS	1	n/a	✗	—	—	—
Keystone	KTEB-126-1-TP-SC-RJS /HB	PS	1	n/a	✗	—	—	—
Keystone	KTEB-218-UV-PS-DW	PS	1	Series	✗	✗	—	—
Keystone	KTEB-218-UV-RS-DW	RS	1	Series	✓	✓	—	—
Keystone	KTEB-226-1-TP	PS	2	Series	—	—	✗	—
Keystone	KTEB-226-UV-PS-DW	PS	2	Series	✗	✗	✗	✗
Keystone	KTEB-226-UV-RS-DW	RS	2	Series	✗	✗	✓	✓
Keystone	KTEB-242-UV-RS-DW	RS	2	Series	✗	✗	✗	✗
Motorola	M2-CF-26-B-S-277	RS	2	Series	—	—	—	✓
Philips Advance	ICF-2S26-H1-LD	PS	2	Series	✓	✓	✓	✓
Philips Advance	ICF-2S26-M1-BS	PS	2	Series	✓	✓	✓	✓
Philips Advance	ICF-2S42-M2-LD	PS	2	Series	—	—	✓	✗
Philips Advance	IZT-2S26-M5-LD	Dimming PS	2	Series	✓	✓	✓	✓
Philips Advance	RCF-2S26-M1-LS-QS	RS	2	Series	✓	—	✓	—
ProLume	EP2CF18PS/MV/DC/K	PS	1	Series	✗	✗	—	—
ProLume	EP2CF26PS/MV/DC/K	PS	2	Series	✗	✗	✗	✗
Robertson	RSQ142TR120	RS	1	Series	✗	—	—	—
Sunpark	U-226PS-W	PS	2	Series	✓	✓	✓	✓
Sylvania	QTP 2×26/32/42CFUNV DM	PS	2	Series	—	—	✓	✓
Sylvania	QTP 2×26/32/42CFUNV DM PEM	PS	2	Series	—	—	✓	✓
Sylvania	QTP 2×26CF/UNV BS	PS	2	Series	✓	✓	—	✓
Sylvania	QTP 2×26CF/UNV DM	PS	2	Series	✓	✓	✓	✓
Tospo	TP120-2/26 RS UPL	RS	2	Series	—	—	✗	—
Universal Lighting Technologies	C2642UNVBE	PS	2	Series	✓	✓	✓	✓
Universal Lighting Technologies	C2642UNVME	PS	2	Series	✓	✓	✓	✓

Applies to the following Satco Products:

S21410, S21412

✓	Compatible
✗	Not Compatible
—	Not Applicable

Important Notice: Ballast testing is performed using a specific manufacturing date code. Ballasts with the same model number but different production dates may have different electronic designs, which can affect compatibility. Likewise, newer ballasts with the same model number may have design revisions that impact performance. Compatibility may also extend beyond this list. SATCO recommends testing a small number of fixtures with the lamps—even when the ballast appears on the compatibility list—to confirm proper compatibility and performance. All data subject to change without notice.

This list is current as of Mar. 2026. We are continuously testing for compatible ballasts. Please check back for updates.

110 Heartland Blvd.
Brentwood, NY 11717
PH 631-243-2022
FX 631-243-2027

Distribution Centers
New York, Florida,
Texas, Washington,
California, Puerto Rico

National Toll-Free
800-43-SATCO
(800-437-2826)
www.satco.com

Copyright© 2026
Satco Products, Inc.
All Rights Reserved.
Rev: March 16, 2026